



The APart SVC4 is a unique multiple stereo volumecontrol. It gives you the possibility to adjust (or switch off) the volume in 4 different zones. To be used with a standard HiFi amplifier.

ATTEND ! In case you only want to adjust 2 zones, you can use traditional 8 Ohm loudspeakers. If you want to adjust the volume in 3 or 4 zones, you have to use 16 Ohm loudspeakers. You may use 2 loudspeakers per zone.

The SVC4 uses internal resistors. In this way you can adjust (or switch off) the volume in 1 zone, without influencing the volume (impedance) in the other zones.

Built-in in a compact black metal housing. Very durable due to the step-by-step volumecontrol-buttons.

## TECHNICAL SPECIFICATIONS

Type	Metal
Handling power	16 Ohm loudspeakers: 4 x (2 x 40) watt 8 Ohm loudspeakers: 2 x (2 x 40) watt
Impedance	2 x 4 Ohm
24V priority	No
Attenuation steps	6 + on/off switch
Dimensions (H x W x D)	46 x 210 x 185 mm
Weight	1.1 Kg
colour	Painted black